


	Order no.	Packing unit	PS
	Instabus KNX/EIB heating actuator, 6-gang 0.05 A		
DRA plus	1018 00	1	26

Product family: Output
Product type: Binary output, 6-gang
 6-gang DRA heating actuator with integrated bus coupler. For switching electrothermic valve drives for heating systems. The heating actuator is equipped with 6 electronic outputs which can control valve drives in dependence on Instabus telegrams. In the process, up to 4 electrothermic valve drives can be connected per output. Installation on DIN cap rail.

The outputs can be controlled either with switching or with pulse-width modulation (PWM). Separate overload and short-circuit detection for each output.

The function of the actuator can also be tested without bus voltage. In the unprogrammed state, pulse width modulation with a corrected variable of 50 % and a cycle time of 15 minutes are already stored in the actuator.


Features which can be set via software:

- 6 independent outputs, each controllable with a corrected variable (1 bit or 1 byte)
- Status feedback (1 bit or 1 byte) per output automatically or on read request
- Valve control (open/closed while deenergised) can be configured for each output
- Summer or winter operation can be selected via an object
- Cyclical monitoring of the corrected variable of each output; if a corrected variable telegram remains off within a monitoring period, the affected output switches into the emergency mode and an alarm message is sent
- Each output can be locked in a forced position, and different values are possible for summer and winter operation
- Behaviour when the bus voltage returns and fails can be configured separately for each output
- Overload or short-circuit message via an object can be set separately for each output
- Mains failure message via an object
- Group message when all valves are closed
- Object for feedback of largest 1 byte corrected variable of an output stored in the actuator

Switching contact: 6 x Triac
 Rated voltage: 230 V AC, 50/60 Hz
 Switch-on current: max. 1.5 A
 Rated current: 0.05 A ohmic load
 Connections: Instabus via connection and branch terminal **0595 00**
 load via screw terminals
 0.2 to 4 mm² single-wire
 2 x 0.2 to 2.5 mm² single-wire
 0.75 to 4 mm² fine-wire without core jacket
 0.5 to 2.5 mm² fine-wire with core jacket
 Operating temperature: -5 °C to +45 °C
 (Cannot be used in heating circuit distributors)
 Protection type: IP 20
 Dimensions: DRA device, 4 depth modules

Thermal valve drive 230 V 1122 00 → Page 375.

Instabus connection and branch terminal 0595 00 → Page 377.

	Order no.	Packing unit	PS
	Instabus KNX/EIB switching actuator, 8-gang 16 A with manual activation		
DRA plus	1006 00	1	26

Product family: Output
Product type: Binary output, 8-gang
 8-gang DRA switching actuator with integrated bus coupler. For switching eight independently controllable groups of loads. Installation on DIN cap rail. With manual switch for switching over the relay (On/Off) parallel or without KNX/EIB operation. No additional power supply. The ETS3.0d is recommended for configuring and commissioning the device. Multi-phase connection.

Functions:

- Independent switching of the 8 outputs.
- Manual actuation of the relay independent of the bus/switching position display.
- NO contact or NC contact operation.
- Central switching function.
- Group feedback for reduction of bus load.
- Active or passive (object can be read out) cyclical feedback function.
- Feedback can be delayed until after the return of bus voltage.
- Logical linking function for each output.
- Block function can be parameterised for each channel. As an alternative, forced setting function for each output.
- Time functions (switch-on, switch-off delay, staircase light function - also with advance warning function).
- Inclusion in light scenes possible, maximum of 8 internal scenes can be parameterised per channel.
- Memory function for light scenes.
- Elapsed-hours meter as forward/backward counter with limit function (limit can be changed via bus) can be activated for each output.
- Input monitoring for cyclical updating with safety setting.
- Reactions in case of bus voltage failure and restoration can be set for each channel following an ETS programming process.

Switching contact: Relay with 8 x zero-voltage closing contacts

Loading capacity
 AC 230 V: 16 A / AC 1 or 10 A / AC 3

Loading capacity
 AC 400 V: 10 A/AC 1 or 6 A/AC 3

DC switching capacity: 16 A/24 V
 Max. switch-on current: 400 A, 150 µs
 200 A, 600 µs

Connected load: 3600 W ohmic load
 16 A, max. 140 µF capacitive load AC 230 V
 2500 W light bulbs
 2500 W HV halogen
 1200 VA LV halogen, wound transformer
 1500 W LV halogen, Gira Tronic transformer
 2500 VA fluorescent lamps, not compensated
 2300 VA fluorescent lamps duo-circuit
 1300 VA fluorescent lamps, parallel-compensated
 2000 W mercury-vapour lamps, uncompensated
 2000 W mercury-vapour lamps, parallel compensated

Connections: Instabus via connection and branch terminal **0595 00**
 load via screw terminals
 0.2 to 4 mm² single-wire
 2 x 0.2 to 2.5 mm² single-wire
 0.75 to 4 mm² fine-wire without core jacket
 0.5 to 2.5 mm² fine-wire with core jacket

Dimensions: DRA device, 8 depth module

Instabus connection and branch terminal 0595 00 → Page 377.